


NASA TECH BRIEF

Marshall Space Flight Center



NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the National Technical Information Service, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Office, NASA, Code KT, Washington, D.C. 20546.

Synchronous Ten-Megabit Biphase Detector



The problem:

In the Space Station data-management system, ten megabit biphase data is frequency-division multiplexed (FDM) over a coaxial cable data bus. A model of the system is now under concept verification testing. The FDM process requires MODEMS (modulator/demodulators) that employ filters for channel selection. Distortion is caused by these filters as well as by couplers and imperfect cable and circuitry. The distorted data makes it impossible to generate a jitter-free clock directly from the data and correctly decode the biphase signal.

The solution:

A synchronous phase-lock-loop detector was designed to accept the distorted input and to generate a jitter-free clock. The data-detection circuitry takes advantage of this clock and employs an integrate-and-dump decision circuit to provide near-theoretically ideal data decoding.

How it's done:

The 10-MHz biphase data is accepted by the synchronous detector and is preconditioned by differentiation and rectification logic (see figure).

This logic generates a short pulse for each data transition and consequently produces a frequency spectrum to the phase-lock-loop that contains continuous-frequency components. The phase-lock-loop synchronizes to the 20-MHz component and accordingly locks to the

phase of the incoming data. The phase-lock-loop provides filtering and does not follow the instantaneous transition variations of the distorted data. The 20-MHz output is "divided by two" to produce the required 10-MHz jitter-free clock output. Advantage is taken of the nearly ideal phase-lock-loop clock to implement an integrate-and-dump data detector.

Notes:

Requests for further information may be directed to:
Technology Utilization Officer
Marshall Space Flight Center
Code A&PS-TU
Marshall Space Flight Center, Alabama 35812
Reference: B73-10323

Patent status:

Inquiries concerning rights for the commercial use of this invention should be addressed to:

Patent Counsel
Marshall Space Flight Center
Code A&PS-PAT
Marshall Space Flight Center, Alabama 35812

Source: L. Balliet of
IBM Corp.

under contract to
Marshall Space Flight Center
(MFS-22546)

Category 02